

ELECTRICAL

- ☐ Do you specify compliance with HIOSH for all contract electrical work?

Action to be Taken

Assigned To:

- ☐ Are all employees required to report as soon as practicable any obvious hazard to life or property observed in connection with electrical equipment or lines?

Action to be Taken

Assigned To:

- ☐ Are employees instructed to make preliminary inspections and/or appropriate tests to determine what conditions exist before starting work on electrical equipment or lines?

Action to be Taken

Assigned To:

- ☐ When electrical equipment or lines are to be serviced, maintained or adjusted, are necessary switches opened, locked-out and tagged whenever possible?

Action to be Taken

Assigned To:

- ☐ Are portable electrical tools and equipment grounded or of the double insulated type?

Action to be Taken

Assigned To:

- ☐ Are electrical appliances such as refrigerators, vacuum cleaners, polishers, vending machines, etc., grounded?

Action to be Taken

Assigned To:

- ☐ Do extension cords being used have a grounding conductor?

Action to be Taken

Assigned To:

- ☐ Are adapters, which interrupt the continuity of the equipment grounding connection, prohibited?

Action to be Taken

Assigned To:

Electrical

- ☐ Are ground-fault circuit interrupters installed on each temporary 15 or 20-ampere, 120 volt AC circuit at locations where construction, demolition, modifications, alterations or excavations are being performed?

Action to be Taken

Assigned To:

- ☐ Are all temporary circuits protected by suitable disconnecting switches or plug connectors at the junction with permanent wiring?

Action to be Taken

Assigned To:

- ☐ Do you have electrical installations in hazardous dust or vapor areas? If so, do they meet the National Electrical Code (NEC) for hazardous locations?

Action to be Taken

Assigned To:

- ☐ Is exposed wiring and cords with frayed or deteriorated insulation repaired or replaced promptly?

Action to be Taken

Assigned To:

- ☐ Are flexible cords and cables free of splices to taps?

Action to be Taken

Assigned To:

- ☐ Are clamps or other securing means provided on flexible cords or cables at plugs, receptacles, tools, equipment, etc., and is the cord jacket securely held in place?

Action to be Taken

Assigned To:

- ☐ Are all cord, cable and raceway connections intact and secure?

Action to be Taken

Assigned To:

- ☐ In wet or damp locations, are electrical tools and equipment appropriate for the use or location or otherwise protected?

Action to be Taken

Assigned To:

Electrical

- ☐ Is the location of electrical power lines and cables (overhead, underground, under floor, other side of walls, etc.) determined before digging, drilling or similar work is begun?

Action to be Taken

Assigned To:

- ☐ Are metal measuring tapes, ropes, handlines or similar devices with metallic thread woven into the fabric prohibited where they could come in contact with energized parts of equipment or circuit conductors?

Action to be Taken

Assigned To:

- ☐ Is the use of metal ladders prohibited in areas where the ladder of the person using the ladder could come in contact with energized parts of equipment, fixtures or circuit conductors?

Action to be Taken

Assigned To:

- ☐ Are all disconnecting switches and circuit breakers labeled to indicate their use or equipment served?

Action to be Taken

Assigned To:

- ☐ Do all interior wiring systems include provisions for grounding metal parts of electrical raceways, equipment and enclosures?

Action to be Taken

Assigned To:

- ☐ Are all electrical raceways and enclosures securely fastened in place?

Action to be Taken

Assigned To:

- ☐ Are all energized parts of electrical circuits and equipment guarded against accidental contact by approved cabinets or enclosures?

Action to be Taken

Assigned To:

- ☐ Is sufficient access and working space provided and maintained about all electrical equipment to permit ready and safe operations and maintenance?

Action to be Taken

Assigned To:

Electrical

- ☐ Are all unused openings (including conduit knockouts) in electrical enclosures and fittings closed with appropriate covers, plugs or plates?

Action to be Taken

Assigned To:

- ☐ Are electrical enclosures such as switches, receptacles, junction boxes, etc., provided with tight-fitting covers or plates?

Action to be Taken

Assigned To:

- ☐ Is each motor disconnecting switch or circuit breaker located within sight of the motor control device?

Action to be Taken

Assigned To:

- ☐ Is each motor located within sight of its controller or the controller disconnecting means capable of being locked in the open position or is a separate disconnecting means installed in the circuit within sight of the motor?

Action to be Taken

Assigned To:

- ☐ Are employees who regularly work on or around energized electrical equipment or lines instructed in the cardiopulmonary resuscitation (CPR) methods?

Action to be Taken

Assigned To:
